

SUPERPRINT *PRO80*[™] QUICK GUIDE

This Quick Guide contains basic information.
For complete instructions, see the manual.

Special Function Buttons (page 4-5 of manual)

Esc (Escape)	Exit current menu and return to Standby mode.	Send Memo	Send a Memo that is stored in the Memo directory.
Options	Select the option that you wish to personalize.	Greeting	Send the Greeting message.
Printer	Turn the printer on or off.	Emergency	Dial the number for an emergency. THIS IS PRE-PROGRAMMED WITH “911.”
Auto-Answer	Turn Auto-Answer on or off.	Relay	Automatically dial your Relay service.
Caller ID	Review Caller ID entries.	Dial	Begin process for dialing a telephone number.
Clear	Clear the memory of one function or all functions.	On/Off	Turn Superprint <i>Pro80</i> on or off. Also hangs up a call.
Relay Voice	Send a voice message that says to use a text telephone or dial through Relay.		

Connecting Power & Phone Line (page 7)

First-Time Setup
Pull the plastic tab out of the battery compartment and gently pull the printer guard out of the printer compartment.

Safety Instructions
Please read and follow the Safety Instructions located on page iii of the manual.

Phone Line
Plug one end of the telephone line into a telephone wall outlet.

Telephone or Signaler
Plug the other end of the telephone line into either telephone jack on the back of the Superprint Pro80.

Power
Plug the AC adapter cord into the jack on the back of the Superprint Pro80.

AC Adapter
Plug the AC adapter into an electrical outlet.

Setting Date & Time (page 10)

1. Press **Options**.

CODE <AUTOMATIC>

2. Press **↓** until you see:

SET THE CLOCK <NO>

3. Press the **Spacebar**.

SET THE CLOCK <YES>

4. Press **Enter**.

01/01/98 12:00 AM

5. Type each number.

12/01/98 12:00 AM

6. To change AM or PM, press **A** or **P**.

Loading Paper (page 9)

Before Loading Paper
First, notice how the paper holder is installed. This may come off while loading the paper. Second, connect power.

Step 5
Put the paper on the metal holder and snap the holder onto the bottom of the Superprint Pro80.

Step 4
Feed the paper through the slot in the printer cover. Put the cover back on.

Step 3
Turn on the Superprint Pro80 and press the **Enter** key several times until the rollers grab the paper and feed it through the printer.

Step 2
With the paper coming off the bottom of the roll, facing the back of the Superprint Pro80, feed the edge of the paper into the slot on the back until it stops.

Step 1
Take off the printer cover: Lift the back edge up toward the keyboard. Then, lift off the cover.

12/15/98 11:56 PM

7. Press **Enter**.

TIME AND DATE SAVED

8. Press **Esc**.

TTY ON


Placing a Call (page 11)

- 1. Press Dial .
TYPE NAME OR NUMBER>
- 2. Type the telephone number.
DIAL> 5551234
- 3. Press Enter .
DIALING...5551234
- 4. Wait for answer.
HELLO JOHN HERE GA
- 5. Begin your conversation.
HI THIS IS JANE HOW IS
- 6. Press On/Off to end the conversation.

Redialing (page 13)

- 1. Press Dial .
TYPE NAME OR NUMBER>
- 2. Press Enter .
REDIALING...5551234

Answering a Call (page 16)

- 1. The Ring Flasher flashes to let you know you have a call.
 ...LINE IS RINGING...
- 2. Type your greeting.
HELLO JANE HERE GA
- 3. Press On/Off to end the conversation.

Using the Emergency Button (page 21)

NOTE: This button is pre-programmed to dial **911**.

Programming the Emergency Number

- 1. Hold down the Program key and press Emergency .
EMERGENCY NUMBER> 911
- 2. Press Clear .
EMERGENCY NUMBER>_
- 3. Type desired number.
EMERGENCY NUMBER> 555-1234
- 4. Press Enter .
** EMERGENCY NUMBER SAVED **

Calling the Emergency Number

- 1. Press Emergency .
DIALING EMERGENCY NUMBER
- 2. Wait for dialing.
DIALING...911
- 3. Wait for answer.
911 CAN I HELP YOU Q GA
- 4. Begin your conversation..
HELLO THIS IS MR SMITH
- 5. Press On/Off to end the conversation.

Using the Directory (page 27)

Saving a New Number

- 1. Hold down the Program key and press Directory .
TYPE NAME OR UP/DOWN TO SEARCH
- 2. Type a new name and press Enter .
PHONE NUMBER>_
- 3. Type desired number.
PHONE NUMBER> 555-1234
- 4. Press Enter .
DIRECTORY ENTRY SAVED

Calling a Directory Number

- 1. Press Dial .
TYPE NAME OR NUMBER
- 2. Type the desired name.
DIAL> JOHN SMITH
- 3. Press Enter .
DIALING...555-1234
- 4. Wait for answer.
HELLO JOHN HERE GA
- 5. Begin your conversation.
HI THIS IS JANE HOW IS
- 6. Press On/Off to end the conversation.

Using Memos (page 25)

Saving a New Memo

1. Hold down the **Program** key and press **Send Memo**.
EDIT MEMO>
2. Type a new Memo name and press **Enter**.
PIZZA>_
3. Type desired message.
PIZZA> PEPPERONI, MUSH
4. Press **Enter**.
**** MEMO SAVED ****

Sending a Memo

1. Press **Send Memo**.
SEND MEMO>
2. Type the name of the Memo.
SEND MEMO> PIZZA
3. Press **Enter** to send the Memo.
PEPPERONI, MUSHROOMS

Using Auto-Answer (page 29)

Turning On Auto-Answer

1. Press **Auto-Answer**.
AA ON 0 NEW MESSAGES
2. Leave the Superprint *Pro80* turned on.
3. Press **Esc** at any time to turn off Auto-Answer.

Reviewing Messages

1. Auto-Answer must be on.
AA ON 3 NEW MSGS
2. Press **↵** to begin reviewing.
YOU HAVE 03 MESSAGES,
3. Review all messages.
----- <END OF MESSAGES>
4. Press **Esc**.
CLEAR MESSAGES <NO>
5. To clear messages, press the **Spacebar**.
CLEAR MESSAGES <YES>
6. Press **Enter**.
**** MESSAGES CLEARED ****

Using Caller ID* (page 35)

Turning On Caller ID

1. Hold down the **Program** key and press **Caller ID**.
Caller ID <OFF>
2. Press the **Spacebar**.
Caller ID <ON>
3. Press **Enter**.
**** CALLER ID IS ON ****
4. Leave the Superprint *Pro80* turned on.

**Requires Caller ID service from your telephone company.*

Reviewing Entries

1. Caller ID should be on.
3 NEW CALLS
2. Press **↵** to begin reviewing.
1 ULTRATEC INC 238-5400
3. Press the **Spacebar** to view date and time (if available).
1 238-5400 11/03 9:30 AM
4. Continue to review until you see:
**** END OF LIST ****
5. Press **Esc**.
0 NEW CALLS

Hot Keys

3-Way Calling	<div>Ctrl</div> + <div>Shift</div> + <div>F</div>	p. 23	Sticky Keys	<div>Shift</div>	(5 times)	p. 47
Baudot	<div>Ctrl</div> + <div>Shift</div> + <div>B</div>	p. 23	Time Display	<div>Ctrl</div> + <div>T</div>		p. 10
Hang Up	<div>Ctrl</div> + <div>Esc</div>	p. 16	Voice Announcer	<div>Ctrl</div> + <div>Spacebar</div>		p. 20
Hook Flash	<div>Shift</div> + <div>1</div>	p. 15	Wait for Response	<div>Ctrl</div> + <div>Shift</div> + <div>W</div>		p. 23
Reset	<div>Shift</div> + <div>Shift</div> + <div>Ctrl</div>	p. 55				